

# SC JOYSTICK MAPPER QUICK REFERENCE GUIDE V 2.17

20151227 – Cassini

- <https://github.com/SCToolsfactory/SCJMapper-V2/releases>
- Change Log: see ReadMe.txt

SC Joystick Mapper - V 2.17.0.50 beta

by Cassini

For information and updates visit us @ Github...

pp\_rebindkeys layout\_my\_x55\_abox\_a3

spaceship\_general

- v.reject -js3\_rant -button24
- v.left -js3\_button23
- v\_self\_destruct
- v.toggle\_cabin\_lights - js3\_button18
- v.toggle\_running\_lights - js3\_button22

spaceship\_view

- v.view\_yaw\_left
- v.view\_yaw\_right
- v.view\_yaw
- v.view\_pitch\_up
- v.view\_pitch\_down
- v.view\_pitch
- v.view\_cycle\_fwd - js3\_button13
- v.view\_cycle\_internal\_fwd
- v.view\_option
- v.view\_mode - js3\_button17
- v.view\_zoom\_in
- v.view\_zoom\_out
- v.view\_interact
- v.view\_cycle\_headlook\_mode - js3\_button21
- v.view\_toggle\_headlook\_mode
- v.view\_dynamic\_focus
- v.view\_dynamic\_focus\_in
- v.view\_dynamic\_focus\_out
- v.view\_look\_behind - js2\_hat1\_down

spaceship\_movement

- v.pitch\_up
- v.pitch\_down
- v.pitch - js2\_v
- v.yaw\_left
- v.yaw\_right
- v.yaw - js2\_x
- v.roll\_left
- v.roll\_right
- v.roll - js2\_rotz
- v.toggle\_yaw\_roll\_swap
- v.throttle\_toggle\_minmax
- v.throttle\_zero - js3\_button42
- v.throttle\_100
- v.throttle\_up
- v.throttle\_down
- v.throttle\_ahc - iCR\_clickart

Joystick 1 Joystick 2 Joystick 3

Saitek Pro Flight X-55 Rhino Stick

# Axis: 3 # POV: 1

# Buttons: 17

Joystick State

X-Achse: 10 Slider 1: 0

Y-Achse: -13 Slider 2: 0

Z Axis: 0 Mehrwegescl -1

X Rotation: 0 POV 2: -1

Y Rotation: 0 POV 3: -1

Z Rotation: -1 POV 4: -1

Buttons: 15

JSN - Assignment

This device is listed as: js2

Cmd: ...

Ctrl: js2\_lalt+button15

Assign Throttle Find list.

Blend JS / kbd Clear

Dump XML-> <- Grab XML

Dump List->

Dump Log->

Device Tuning

Inv. Aim Pitch  Inv. Strafe lateral

Inv. View Pitch  Inv. Strafe longitudinal

Inv. Aim Yaw

Inv. View Yaw

Inv. Throttle

Inv. Strafe vertical

Mapping name: layout\_my\_x55\_abox\_a3

Profiles: Reset... Support: profile version="1" optionsVersion="2" rebindVersion="2" Mappings: layout\_my\_x55\_abox\_a3 Load...

Profiles: Reset... Support: profile version="1" optionsVersion="2" rebindVersion="2" Mappings: layout\_my\_x55\_abox\_a3 Load...

Disclaimer: Usual stuff – no warranty whatsoever..

Freeware – made for the SC community

Hope it helps and does not suck.

Have fun in the verse ...



# General Information

- Connect the game control devices to the PC
- Start from scratch or load an existing map from a file
- Make or refine mappings
- Save the new map as an XML file
- Use it in the game: e.g. `pp_rebindkeys layout_my_joystick`
- You may load and save the map directly from your game folders  
so next time you just use `pp_rebindkeys layout_my_joystick`

Note: the predefined actions are the ones found in the SC game default profile – it is likely that some of them will not work at all as the game is not finished. There is no proper description for which one does what – you may get help in SC Forums.

BTW: if you copy e.g. “`pp_rebindkeys layout_my_joystick`” from notepad you may use Ctrl-V to paste it in-game into the console – saves you some typing...


Console .. Opens with the top left key usually right below the “Esc” key  
- depends on your keyboard

If you encounter an error or crash then read on...

- ◆ You will find ‘log4net.config.OFF’ in the distribution zip.
- ◆ Rename it to ‘log4net.config’ and run the program.
- ◆ Then look for a file named ‘trace.log’ in the program folder and
- ◆ send this to [cassini@burri-web.org](mailto:cassini@burri-web.org) along with a description of the problem and your system i.e. OS, CPU, Graphics card, Joystick(s)
- ◆ we may then finally solve the issue ...


# SCJMapper V 2 – Common Workflows

## The Workflow




# The GUI

The user interface is all laid out for direct access — there are no menus



# Game Devices




The tabs represent the game devices found connected to the PC. The program can show up to 9 devices.

The sequence 1..8 shows the order the PC reports them which is crucial to the mapping as this will result in the default js1\_, js2\_ .. Names used to build the command name.

A summary of the capabilities is shown in the top area.

A tooltip indicates the real name of the device - move and point the mouse to any Tab to show the indicator.



The elements shown in 'Joystick State' are the ones the device seems to support – greyed ones are not available for this device.

You will see the actual jsN assignment - or 'not assigned'.

The SC-Device to Joystick Mapping is a separate window accessed by hitting the 'Js Reassign' button.

Just hit any button, Axis of the device and see how things are changing.

Note: the range for Axis is set to -1000 .. +1000 by the program and is not what other applications may show you.

# Action Tree and mappings

## Action Tree

The action tree is initially built from the games defaultProfile - so these are the known actions which are grouped along 'action maps' e.g. 'spaceship\_movement'.

Each action is predefined for a specific device.

There are joystick, keyboard, mouse, and gamepad actions indicated by the icon. – This is given by the SC default profile and cannot be changed. An action may e.g. not be available for the joystick.

## Rebinding:

By 'rebinding' or mapping and action with a different control one does replace the default one.

Overwriting a keyboard action will result in having it available with a different command in the game.

You can only map actions using the same device as in the profile i.e. a keyboard action cannot be mapped with a joystick control.

If actions are mapped (as shown) the color indicates which device is mapped.

The device tab colors match the entries, keyboard and mouse have distinct colors.

If the background is white - there is no current mapping given.

Unmapped actions are ignored.


## Selecting an Action:

Click on any action to make it the used action in the mapping area. Once selected it is marked with the green arrow



A regular action tree

# Action Tree Filters




## Action Tree Filters

The action tree has a vast number of entries. So for convenience you may filter the shown items to the one you are interested in.

## Device Filter


With the checkboxes at the bottom you may restrict the shown item to a particular category.



Check categories you want to see


## Mapped Only

Restricts to show only mapped items



## Action Filter

Accepts text entry to match parts of the



action name

## Clear Filter

To empty the field

NOTE: Filters only restrict the items shown in the tree

# Working with Profiles




## Working with profiles

The program gets the actions from the real game asset – so you are always up to the actual values.

From here you may Reset the action list to the following




-RESET EMPTY reverts to just an action list without any mappings

-RESET DEFAULTS loads the Joystick actions mapped with what CIG is providing





# Mapping



Whenever you click on an action in the Action Tree it is copied into Cmd. and can be mapped to a Control. The Control (Ctrl.) is the last item you activated on the currently shown device tab. You may also map keyboard and mouse actions.

## Devices vs. Keyboard/Mouse

To switch between game devices and keyboard/mouse use the 'JS/Kbd' toggle. Note: keyboard entries are accepted when the Ctrl. Field has the focus

### Select the device

To map a device control first select the device tab i.e. if you want to map a control of the second joystick you have to select the 'Joystick 2' Tab first.

### Assign

Once you have a mapping that should be used, hit the "Assign" button. The new mapping will be shown in the Action Tree – where it gets the back color of the device it is assigned to.

### Throttles

To make any axis a Throttle axis – check the 'Throttle' box ! It is often the Z-Axis. A throttle gets a name like js2\_throttlez.

### Clear Actions


To clear a mapping – select it in the ActionTree and Click "Clear" - it gets a neutral color and no control in the ActionTree – it is now unmapped.

### Find a mapping

You may use "Find 1st" to find the first action where the currently shown Ctrl.

### Blending

If you wish to blend a single item from the defaultProfile i.e. hide it from use select an item and then hit the 'Blend' button.



# More Mapping

## Context Menu


Right click an action opens a context menu giving a choice of functions that are possible right now.

**Assign, Blend, Clear** behave like the buttons in the main GUI

## Add Mapping



Will add a binding to the selected item to use a second control for this item. Such an addition can be mapped like the main entry - also deleted to remove it.

(Note: this does not work in SC2.0/2.1)



## Activation Modes

Starting from Profile: there are activation modes listed. Profile indicates what is in the profile as default or 'no ActivationMode' if the profile does not apply one






You may choose a new activation mode

```
<actionmap name="spaceship_view">
  <action name="v_view_cycle_headlook_mode">
    <rebind input="js3_button21" ActivationMode="double_tap">
    </action>
  <action name="v_view_toggle_headlook_mode">
    <rebind input="js3_rctrl1+button21" />
  </actionmap>
```

for this mapping which is then carried into the XML

Most notable are double\_tabs which may be applied by CIG in the profile sometimes and are then carried into the mapping if not changed here.

# Mapping with Modifiers



## Keyboard Modifiers

Controls can be extended with a Modifier. Right now only keyboard modifiers can be used for joysticks.

Modifiers are preset:

Left/right Shift / Alt / Ctrl keys

Modifiers can be combined.

If you press a modifier it will show up like 'lshift+lctrl+key'

For devices the notation is different - it is prepended by the device tag

E.g. js2\_lalt+y (js2\_y is the control that is modified here)

For keyboard input press all keys and release them at once.

Sometimes a second attempt is needed to create the proper key sequence.

## Clear Modifiers

To clear all modifiers from the input


**Press the ESC key for a moment.**

# XML Dump

## XML Format

Mappings are sent to the game using XML formatted files.

The XML Area is where you may find the mapping after hitting the 'Dump' button.



## The Context Menu

Right click opens a menu where you may choose from:

Copy, Paste, PasteAll, Select All, Open..., Save As...

The usage is rather common here. Once you dumped the mapping you want to "Save" it as "filename.xml" somewhere.

To refine any mapping "Open" the file – the content is shown in the XML Area, then "Grab" it into the ActionTree. Once the refinement is finished – again Save it to a file.

Note: only use properly formatted ActionMaps here. The program may just break if it encounters something unexpected!

```
<options type="joystick" instance="2">
  <flight_move_roll exponent="1.00" >
    <nonlinearity_curve>
      <point in="0.182" out="0.028"/>
      <point in="0.629" out="0.235"/>
      <point in="0.895" out="0.629"/>
    </nonlinearity_curve>
  </flight_move_roll>
</options>

<deviceoptions name="Saitek Pro Flight X-55 Rhin
  <option input="x" deadzone="0.025" />
</deviceoptions>

<deviceoptions name="Saitek Pro Flight X-55 Rhin
  <option input="y" deadzone="0.025" />
</deviceoptions>

<deviceoptions name="Saitek Pro Flight X-55 Rhin
  <option input="rotz" deadzone="0.025" />
</deviceoptions>

<actionmap name="spaceship_general">
  <action name="v_eject">
    <rebind input="js3_ralt+button24" />
  </action>
  <action name="v_exit">
    <rebind input="js3_button23" />
  </action>
  <action name="v_toggle_cabin_lights">
    <rebind input="js3_button18" />
  </action>
  <action name="v_toggle_running_lights">
    <rebind input="js3_button22" />
  </action>
</actionmap>

<actionmap name="spaceship_view">
  <action name="v_view_cycle_fwd">
    <rebind input="js3_button13" />
  </action>
  <action name="v_view_mode">
    <rebind input="js3_button17" />
  </action>
</actionmap>
```

XML Dump of an action map

# Action maps

## Working with action maps

(Maps, Mapping etc..)

The program gets the action maps from the USERS game asset – so you are always up to the actual values.

(...\StarCitizen\Public\USER\Controls\Mappings)

From here you may first chose a map, then 'Load' the action map – this will overwrite you XML window in any case




-LOAD loads the map into the XML window only

-LOAD and GRAB loads the map into the XML window and clicks Grab i.e. merges the existing mapping with the one loaded

-RESET, LOAD and GRAB first Reset (empty) the action list (all mappings cleared) then it loads and grabs the new map

-DEFAULT, LOAD and GRAB first Reset (defaults) the action list then it loads and grabs the new map and merges them with the defaults

See page 3 for some common workflows And how to handle them easily.



# Your Actionmaps

## Working with your own actionmaps

The program not only gets the actionsmaps from the real game asset – but also can save your maps there.

(...\StarCitizen\Public\USER\Controls\Mappings)

- 1.Type a name
- 2.Hit the button – it will then Dump and Save your map into the game folder (asking you to overwrite it if it exists)



Remark: your map name has always to start with **'layout\_my\_'** to prevent conflicts with CIGs own actionmaps  
Lowercase only, no spaces, tabs allowed else you see the red flag ..

A successful Save will show the green flag


Your own maps will then show up like the game provided maps  
pp\_rebindkeys layout\_my\_joystick

should load it into the game

Note: For your convenience each Save also makes a copy of into your personal "My Documents\SCJMapper" folder – no work is lost if there is an update that cleans the Mappings folder.



# Settings




There are a number of setting you may need to do for efficient working..

Settings...

## Ignore Buttons


Some devices have buttons pressed to switch modes. I may be needed to 'ignore' them to get proper readouts for mapping.

Enter the numbers with a space between - like in the example below



## Ignore Action maps

You may not want to deal with all the maps provided by the game - check the ones you want to ignore those maps are hidden from you and will not be processed once ignored.



# Settings (2)


## Providing a path to the game

In general the program finds the path to the game on its own, however if not, you may direct it to use a given path




The path should be the top folder of the SC installation

Make sure to check the left box to use the path




## Use Gamepad

The gamepad needs special treatment - if you want to use a gamepad you have to check the box.




## Using PTU Folders


In general the program finds its files in the Public subfolder of the Game installation path. If you are running PTU and want to work with the Test environment - check this box



Changing to and from PTU requires a restart!



Once in PTU mode the program indicates this as shown below





# Joystick Assignment

Joystick	Device Name	Assigned jsN
Joystick 1	vJoy Device	n.a.
Joystick 2	Saitek Pro Flight X-55 Rhino Stick	js2
Joystick 3	Arduino Micro	js3
Joystick 4		
Joystick 5		
Joystick 6		
Joystick 7		
Joystick 8		

(re) assign the joystick devices to the wanted js - number

Js Reassign...

Go here if you wish to assign a device to a particular js – number or to re-assign the devices to other numbers.

Per default the devices found are assigned along the sequence 1..8 but SC may remap them so here is the place to fix this without having to go through all commands and reassign them.

Notes: The color of the assigned items will not change as it is still the same device but js1 will become js2 for example.

You can leave this dialog with “Accept” only if each device is either assigned to a unique number or to n.a. (not assigned) otherwise an error pops to ask you to fix it or Cancel.

Related SC console commands are:

```
i_DumpDeviceInformation
```

```
pp_ResortDevices joystick 1 2
```

```
pp_rebindkeys export joystick  
pp_rebindkeys export xboxpad
```


# Device Tuning 1/3

There are options provided to tune the reaction of a game device


Use 'Device Tuning' to optimize it, it supports:

- Deadzone
- Sensitivity
- Invert
- either Exponent or NonLinearCurve independently for the Yaw-, Pitch-, and Roll- axes.

Note: Tuning will only recognize mapped controls



Hit the 'Device Tuning' button to open the tuning window



**Actual mapping for the axis**

**Live View of the joystick movement**

**Tuning parameters of the axis**

**Tuning parameters of the active axis**

**Joystick IN->OUT map**

**Turnspeed [seconds per full turn]**

**Damping - how fast will a movement stop (1=fast)**

**Activate an axis**

**Live IN - OUT values scaled 0.. 1**

**Changing Skies**

Axis	IN(x)	OUT(y)
Point 1	0.336	0.043
Point 2	0.651	0.236
Point 3	0.880	0.703

# Device Tuning 2/3

**How to...**

There is one active axis – the color frame of the chart indicates the active one (here blue = Yaw) 1

Parameters can be manipulated for the active axis only.

Switch the active one by clicking the Yaw, Pitch, Roll Option (bottom, left) 2

Activating a tuning parameter will activate too 3

Parameters must be 'checked' to be used 3

e.g. Deadzone and NonLinearCurve (Pt1..3) are checked for Yaw

Each axis has it's own set of parameters

Active and Checked (Enabled) parameters can be changed. 3

Deadzone is a simple slider from 0.0 to 0.15 (try it out in the live view)

All other parameters are handled by first choosing it (e.g. Point 1) 4

Changing the value by first left click and hold into the chart area, then moving the mouse up-down and left-right to adjust – then release the mouse button.

Point 1 is usually the leftmost orange marker 5

If you wish to copy the Curve Points to all other axis – click the Copy button 6

Sensitivity and Exponent will only go with up-down movement of the mouse

...

Here Roll (Green) is active and Exponent is chosen to be changed. 1

By click, hold and moving down – the exponent was changed from 1.47 to 2.83

The curve represents IN vs OUT of the joystick

If you move the joystick the 'Live' fields will report what's going on:

Sometimes it is helpful to just disable one direction of the movement 3

Check OFF for any axis (it just disables it for the Live View)

# Device Tuning 3/3

## Once back from Tuning...

With “Dump” or “Dump and Save” you will get the new Tuning values into the XML area – if you don't want to apply the new settings, just hit “Grab” to restart with the settings from the XML area.

With “Dump” the prog will maintain the parameters using the following 2 XML tags

- <options ...>
- <deviceoptions ...> (Deadzone only)

One set for each axis

Note: the program will automatically apply Exponent=“1” if the Exponent is not used – if not set to 1 the game will use something like 2.3 and reshape any setting to an unexpected outcome...

*If you have a 2 monitor setup – you may want to try to have the tuning window open while running AC – the joystick input is then applied to both applications – getting into the console will let you the mouse to interact with the tuning window, create a new tuned map and you may apply it immediately via console rebind to try it out (You may need a fast computer – but then AC needs this anyhow...)*

The screenshot displays the SC Joystick Mapper interface. The top right pane shows XML configuration for a joystick mapping. A yellow box highlights the XML content, and a red arrow points to the <options type="joystick" instance="3"> section. The XML includes device identification, flight move options (pitch, yaw, roll), and deviceoptions for deadzone.

```
<!-- 22.12.2014 17:59:09 - SC Joystick Mapping -->  
<ActionMaps ignoreversion="1"  
  (id)="Saitek X55 Flight Controller" device="joystick"  
  js3="Saitek Pro Flight X-55 Rhino Stick" js3g="6"  
>  
  <CustomisationUIHeader device="joystick" label="h"  
    <options type="joystick" instance="3">  
      <flight_move_pitch exponent="1.00" >  
        <nonlinearity_curve>  
          <point in="0.182" out="0.028"/>  
          <point in="0.629" out="0.235"/>  
          <point in="0.895" out="0.629"/>  
        </nonlinearity_curve>  
      </flight_move_pitch>  
    </options>  
    <options type="joystick" instance="3">  
      <flight_move_yaw exponent="1.00" >  
        <nonlinearity_curve>  
          <point in="0.182" out="0.028"/>  
          <point in="0.629" out="0.235"/>  
          <point in="0.895" out="0.629"/>  
        </nonlinearity_curve>  
      </flight_move_yaw>  
    </options>  
    <options type="joystick" instance="3">  
      <flight_move_roll exponent="1.00" >  
        <nonlinearity_curve>  
          <point in="0.182" out="0.028"/>  
          <point in="0.629" out="0.235"/>  
          <point in="0.895" out="0.629"/>  
        </nonlinearity_curve>  
      </flight_move_roll>  
    </options>  
    <options type="joystick" instance="2">  
      <flight_throttle invert="1" />  
    </options>  
  </deviceoptions name="Saitek Pro Flight X-55 Rhin  
    <option input="x" deadzone="0.025" />  
  </deviceoptions>  
</ActionMaps>  
</CustomisationUIHeader>  
</>
```

The bottom pane shows device tuning options for the joystick. A yellow box highlights the 'Dump and Save my Mapping' button.

<input type="checkbox"/> Inv. Flight Pitch	<input type="checkbox"/> Inv. Flight Roll
<input type="checkbox"/> Inv. Aim Pitch	<input checked="" type="checkbox"/> Inv. Throttle
<input type="checkbox"/> Inv. View Pitch	<input type="checkbox"/> Inv. Strafe vertical
<input type="checkbox"/> Inv. Flight Yaw	<input type="checkbox"/> Inv. Strafe lateral
<input type="checkbox"/> Inv. Aim Yaw	<input type="checkbox"/> Inv. Strafe longitudinal
<input type="checkbox"/> Inv. View Yaw	


Mapping name: layout\_my\_x55\_65test  
Dump and Save my Mapping

Profiles: defaultProfile Reset... Mappings: layout\_my\_x55\_65test Load...


# Hints ...

## How to get a list of all commands with an action map ?

- Load a map using Defaults



- Hit 'Dump List'



- Gets you the complete list of commands in use if you load that map
- Right click in the listing to get a context menu to Copy / Paste or Save As..


```
-- 27.12.2015 21:34:12 - SC Joystick Mapping --
** js2 = Saitek Pro Flight X-55 Rhino Stick
** js3 = Arduino Micro

*** spaceship_general
v_eject                - js3 - ralt+button24
v_eject                - kb1 - ralt+1
v_eject                - xi1 - trigger1_btn+back
v_exit                 - js3 - button20
v_exit                 - kb1 - lctrl+f
v_exit                 - xi1 - a
v_self_destruct        - kb1 - ralt+backspace
v_toggle_cabin_lights - kb1 - o
v_toggle_running_lights - kb1 - o
skyLine_toggle         - kb1 - m

*** spaceship_view
v_view_yaw_left        - js1 - hat2_left
v_view_yaw_right       - js1 - hat2_right
v_view_yaw             - xi1 - thumbrx
v_view_yaw_mouse       - mo1 - maxis_x
v_view_yaw_absolute    - kb1 - HMD_Yaw
v_view_pitch_up        - js1 - hat2_down
v_view_pitch_down      - js1 - hat2_up
v_view_pitch           - xi1 - thumbry
v_view_pitch_mouse     - mo1 - maxis_y
v_view_pitch_absolute  - kb1 - HMD_Pitch
v_view_roll_absolute   - kb1 - HMD_Roll
v_view_cycle_fwd       - kb1 - insert
v_view_cycle_fwd       - xi1 - trigger1_btn+thumbr
v_view_cycle_internal_fwd - kb1 - home
v_view_mode            - kb1 - pgup
v_view_mode            - xi1 - thumbr
v_view_zoom_in         - mo1 - mwheel_up
v_view_zoom_in         - xi1 - trigger1_btn+dpad_up
v_view_zoom_out        - mo1 - mwheel_down
v_view_zoom_out        - xi1 - trigger1_btn+dpad_down
v_view_interact        - kb1 - f
v_view_interact        - xi1 - a
v_view_cycle_headlook_mode - js3 - button21
v_view_cycle_headlook_mode - kb1 - lalt
v_view_toggle_headlook_mode - js3 - rctrl+button21
v_view_toggle_headlook_mode - kb1 - lalt
v_view_dynamic_focus   - mo1 - maxis_z
v_view_dynamic_focus_in - xi1 - trigger1_btn+dpad_up
v_view_dynamic_focus_out - xi1 - trigger1_btn+dpad_down
v_view_look_behind     - js2 - hat1_down
v_view_look_behind     - kb1 - lctrl+lalt
```

# Hints ...

## How to use pp\_rebindkeys easy in the game ?



- Clicking the Notepad icon top right copies the pp\_rebindkeys command into the Clipboard – from there just Ctrl-V it into the SC console..

Note: if you want to be sure to apply only your new map first type pp\_rebindkeys without a file and then Enter - the response of the game should be - loaded factory defaults ... Then use the command with your mapname (without the .xml extension)

## How to apply keyboard commands and modifiers ?


Sometimes your command is not recognized with the first try

Check the Ctrl field each time and if it does not yet capture what you want – try once more. Also releasing all controls currently pressed **together** helps to get successful Ctrl. Entries.


## What about command you really don't want to be mapped in game ?

Sometimes default commands from CIG annoyingly interfere with your game style

- Load a Profile with defaults and filter if needed to find the problematic action
- If you find that this single kbd leftalt command is disturbing your use of the left alt modifier
- Reload your own map and 'Blend' that action for the keyboard to ignore it in the game







Brought to you by Cassini 2015  
Data and RSI spacecraft are derived work from the RSI homepage